

EV2300 EVM Interface Board

This user's guide describes the function and operation of the EV2300 evaluation module. This guide includes a complete description of the EV2300 EVM, as well as a bill of materials, and schematic.

Contents

1	Introduction	2
2	Interfaces	2
3	EV2300 Bill of Materials, Component Placement, Schematic	6

List of Figures

1	Board Layer 1	8
2	Solder Mask 1	9
3	Solder Mask 2.....	10
4	Board Layer 2.....	11
5	Component Placement 1	12
6	Component Placement 2	13
7	Internal Board Layer 1	14
8	Internal Board Layer 2	15

List of Tables

1	Ordering Information.....	2
---	---------------------------	---

1 Introduction

This EVM interface board enables an IBM-compatible or other type (with required driver for the particular platform) PC to communicate with Texas Instruments SMBus, HDQ, or DQ interface gas gauges via a Universal Serial Bus (USB) port. In addition to this board, PC software is required to interpret the gas gauge data to complete the evaluation system.

1.1 Features

- Fully powered from the USB port
- Capable of providing a 25-mA 3.3-V source
- Complete interface between USB and SMBus, I²C, and HDQ (8/16) interfaces using a simple API

1.2 Kit Contents

- EV2300 circuit module
- Standard USB cable

1.3 Ordering Information

Table 1. Ordering Information

EVM Part Number
EV2300

2 Interfaces

The EV2300 interfaces are described in the following table. The reference designators on the circuit board and the functions are also listed.

Reference Designator	Function	Function
HDQ and SMB	SMBus, HDQ, and DQ Interface ports	Terminal block for connecting to a target device
I ² C	E ² PROM I ² C Interface	Terminal for connecting to a target E ² PROM or I ² C interface battery monitor
USB	USB Interface	Interface to host computer

2.1 Overview

The EV2300 is enclosed and is provided as shown.



2.2 EV2300 Controller

The EV2300 controller is a bq8012 running at 4 MHz. The controller firmware is stored in flash memory and is executed by the core at power-up after the boot ROM code verifies the integrity words.

The controller communicates with target device(s) through either: a 2-wire SMBus communication port, a 1-wire HDQ port, or a 2-wire E²PROM I²C port. The 2-wire SMBus communication port supports both SMBus and I²C protocols.

2.3 USB Interface (USB)

The interface board connects to a USB port (version 1.1) on a host computer and is powered from the port. All communication over the USB is proprietary and does not fit any USB-defined device classes. Therefore communication with the device requires a loader and driver from Texas Instruments.

The loader enumerates the device (determines it is present on the USB), then loads the EV2300 controller firmware for the USB interface. Once the firmware load is complete, the loader sends a command to the USB interface IC to execute the new program and the loader driver exits. A new driver takes control and enumerates the EV2300 and makes the device present to programs running on the host.

The installer for the USB EVB installs:

1. A loader driver
2. A binary to load onto the USB interface IC
3. An EV2300 controller driver for direct access to the device
4. An EV2300 DLL for application access to the device

2.4 HDQ Interface (HDQ)

This interface allows a host computer to interact with a slave or target device through the two-wire SMBus or the one-wire HDQ interfaces. The ports are labeled with the corresponding signal names above each port connector. Connect the signal and a ground reference (GND), and optionally VOUT, to a target device.

The two-wire interface supports SMBus version 1.1 byte, word, block transactions with and without PEC. The SMBus limits the capacitance on each line (Data and Clock) to 100 pF. The EV2300 places 8 pF on each line, so a device may place up to 92 pF total. If the capacitive load approaches or exceeds 100 pF, SMBus communication may not be reliable.

Pin	Name	Description
1	GND	Ground return/reference for HDQ interface
2	VOUT	Controlled EEPROM power. Supplies 5 VDC to a target EEPROM IC
3	HDQ	HDQ one-wire interface. Pulled up to 3.3-V rail with a 10-k Ω resistor
4	VCC	Supplies 3.3 VDC to a target. Current load should be limited to 30 mA

2.5 I²C/EEPROM Interface (I²C)

This interface allows a host computer to interact with a target E²PROM or other I²C interface device such as a battery monitor device through a two-wire I²C interface. The interface contains a controlled power pin, the I²C clock and data lines, and a ground reference.

Pin	Name	Description
1	GND	Ground return. Connected to the SMD and HDQ GND
2	SCL	I ² C clock. This line must be pulled up by the target.
3	SDA	I ² C data. This line must be pulled up by the target.
4	VOUT	Controlled EEPROM power. Supplies 5 VDC to a target EEPROM IC

2.6 SMBus Interface (SMBus)

Pin	Name	Description
1	GND	Ground reference
2	SMBC	SMB clock pin. This pin is pulled to 3.3 VDC through a 10-k Ω resistor. Do not exceed 5.6 VDC on this pin.
3	SMBD	SMB data pin. This pin is pulled to 3.3 VDC through a 10-k Ω resistor. Do not exceed 5.6 VDC on this pin.
4	NC	Not connected on this board. This pin is floating.

3 EV2300 Bill of Materials, Component Placement, Schematic

This chapter includes the schematic, component placement on the circuit board, and a listing of the bill of materials for the EV2300 EVM.

3.1 Bill of Materials (BOM)

Qty	Ref Des ⁽¹⁾	Description ^{(2) (3) (4)}	Size	MFR	Part Number
10	C1-C7, C10-C12, C15, C20	Capacitor, ceramic, 0.1 μ F, 25 V, X7R, 10%	603	TDK	C1608X7R1E104KT
0	C13	Open	603		
2	C16, C21	Capacitor, POSCAP 4.7 μ F, 35 V, 20%	6032 \odot)	AVX	TAJC475K035R
1	C18	Capacitor, ceramic, 2200 pF, 50 V, C0G, 10%	603	TDK	C1608C0G1H222KT
1	C19	Capacitor, ceramic, 150 pF, 50 V, C0G, 10%	603	TDK	C1608C0G1H151KT
2	C8, C9	Capacitor, ceramic, 22 pF, 50 V, C0G, 10%	603	TDK	C1608C0G1H220KT
0	D1-D7, D9, D13-D15, D17	Open	0.068 \times 0.049		
2	D12, D19	Diode, LED, green, 20 mA, 0.9 mcd	0.068 \times 0.049	Panasonic	LN1371G-(TR)
1	D20	Diode, LED, red, 20 mA, 0.9 mcd	0.068 \times 0.049	Panasonic	LN1271R-(TR)
3	D21-D23	Diode, dual, 250 mA, 70 V	SOT23	Vishay-Liteon	BAW56GS08
5	D8, D10, D11, D16, D18	Diode, low capacitance, TVS	SOT23	General Semi	GL05T
1	J1	Connector, USB upstream (Type B)	0.47" \times 0.67"	Molex	67068-1000
3	J13-J15	Header, friction lock assembly, 4-pin right angle	0.400 \times 0.500	Molex	22-05-3041
1	J2	Header, 11 pin, 100 mil spacing, (36-pin strip)	121100	Sullins	PTC36SAAN
0	J3-J5, J8-J11	Open	0.038"		
1	J7	Header, 2 pin, 100 mil spacing, (36-pin strip)	0.100 \times 2"	Sullins	PTC36SAAN
1	Q1	Transistor, NPN, high-performance, 500 mA	SOT23	Fairchild	MMBT2222A
1	Q2	MOSFET, P-ch, -12 V, 4 A, 51 m Ω	SOT23	Vishay	Si2335DS
4	R1, R14, R16, R19	Resistor, chip, 10 k Ω , 1/16 W, 5%	603	Std	Std
12	R13, R15, R21-R24, R26, R27, R45, R46, R49, R50	Resistor, chip, 100 Ω , 1/16 W, 5%	603	Std	Std
3	R18, R42, R43	Resistor, chip, 1 M Ω , 1/16 W, 1%	603	Std	Std
1	R2	Resistor, chip, 15 k Ω , 1/16 W, 5%	603	Std	Std
7	R3-R5, R32-R34, R39	Resistor, chip, 100 k Ω , 1/16 W, 5%	603	Std	Std
3	R30, R51, R52	Resistor, chip, 620 Ω , 1/16 W, 5%	603	Std	Std
2	R31, R41	Resistor, chip, 10 Ω , 1/16 W, 5%	603	Std	Std
1	R35	Resistor, chip, 61.9 k Ω , 1/16 W, 1%	603	Std	Std
1	R53	Resistor, chip, 0 Ω , 1/16 W, 5%	603	Std	Std

⁽¹⁾ Reference designators marked with an asterisk (*) cannot be substituted. All other components can be substituted with equivalent manufacturers components.

⁽²⁾ These assemblies are ESD sensitive, ESD precautions should be observed.

⁽³⁾ These assemblies must be clean and free from flux and all contaminants. Use of no clean flux is not acceptable.

⁽⁴⁾ These assemblies must comply with workmanship standards IPC-A-610 Class 2.

Qty	Ref Des ⁽¹⁾	Description ^{(2) (3) (4)}	Size	MFR	Part Number
1	R54	Resistor, chip, 113 kΩ, 1/16 W, 0.1%	603	Vishay	TNPW06031133BT9R T1
1	R6	Resistor, chip, 1.5 kΩ, 1/16 W, 5%	603	Std	Std
0	R7, R10-R12, R17, R20, R25, R28, R36-R38, R40	Open	603		
2	R8, R9	Resistor, chip, 33 Ω, 1/16 W, 5%	603	Std	Std
0	SW1	Open	5 mm × 5 mm		
2	U1, U2	IC, Single bus buffer gate with 3-state output, with negative enable	DCK	TI	SN74LVC1G125DCK
1	U3	IC, Single bus buffer gate with 3-state output, with positive enable	DCK	TI	SN74LVC1G126DCK
1	U4	IC, USB, general purpose, device controller	0.480 × 0.480"	TI	TUSB3210PM
1	U5	IC, ultra low-power LDO regulator, 3.3 V, 50 mA	SOT23-5	TI	TPS77033DBV
1	U6	IC, Advance gas gauge	DBT38	TI	bq8015DBT
1	Y1 or Y4	Crystal, high performance, 12.00 MHz, SMT	0.126 × 0.126	Citizen or Daishinku	CSA-309-12.000MABJ or DSX630G-12.00 MHz
0	Y2 or Y3	Crystal, 32.768 MHz, 7-12 pF capacitance	1,9 mm × 5 mm	Daishinku or ECS	DST520G-32.768kHz or ECS-0.327-8-14
1	N/A	Plastic enclosure, bone, Texas Instruments silkscreen		PacTec	84107-501-039
		Wire Cable Assembly ⁽⁵⁾			
1	Mate	Connector, female, 0.100 centers		22-01-30 47	Molex
4	N/A	Terminals, crimp, tin		08-50-011 4	Molex
	N/A	Wire, insulated 22 Awg, red, 18 inches (±3 inches) (VOUT)		Any	Any
	N/A	Wire, insulated 22 Awg, white, 18 inches (±3 inches) (SCL)		Any	Any
	N/A	Wire, insulated 22 Awg, black, 18 inches (±3 inches) (GND)		Any	Any
	N/A	Wire, insulated 22 Awg, brown, 18 inches (±3 inches) (SDA)		Any	Any
1	N/A	Heatshrink 1"		Any	Any

⁽⁵⁾ Make one EEPROM connector wire assembly for each assembly produced, from J15 mate, 4 - 22 AWG wires and crimp terminals. Wire colors for pin numbers are listed below. Strip and tin flying leads 0.25 inches from end of wire.
 Red - pin #4 (signal VOUT)
 Brown - pin #3 (signal SDA)
 White - pin #2 (signal SCL)
 Black - pin #1 (GND)

3.2 EV2300 Component Placement




Figure 1. Board Layer 1




Figure 2. Solder Mask 1




Figure 3. Solder Mask 2




Figure 4. Board Layer 2




Figure 5. Component Placement 1




Figure 6. Component Placement 2




Figure 7. Internal Board Layer 1





Figure 8. Internal Board Layer 2

3.3 EV2300 Schematic



Revision History

Changes from A Revision (February 2005) to B Revision Page

- Changed label 3
 - Changed HDQ Interface pin names 4
-

NOTE: Page numbers for previous revisions may differ from page numbers in the current version.

Changes from B Revision (December 2011) to C Revision Page

- Added Schematic 16
-

NOTE: Page numbers for previous revisions may differ from page numbers in the current version.

EVALUATION BOARD/KIT IMPORTANT NOTICE

Texas Instruments (TI) provides the enclosed product(s) under the following conditions:

This evaluation board/kit is intended for use for **ENGINEERING DEVELOPMENT, DEMONSTRATION, OR EVALUATION PURPOSES ONLY** and is not considered by TI to be a finished end-product fit for general consumer use. Persons handling the product(s) must have electronics training and observe good engineering practice standards. As such, the goods being provided are not intended to be complete in terms of required design-, marketing-, and/or manufacturing-related protective considerations, including product safety and environmental measures typically found in end products that incorporate such semiconductor components or circuit boards. This evaluation board/kit does not fall within the scope of the European Union directives regarding electromagnetic compatibility, restricted substances (RoHS), recycling (WEEE), FCC, CE or UL, and therefore may not meet the technical requirements of these directives or other related directives.

Should this evaluation board/kit not meet the specifications indicated in the User's Guide, the board/kit may be returned within 30 days from the date of delivery for a full refund. **THE FOREGOING WARRANTY IS THE EXCLUSIVE WARRANTY MADE BY SELLER TO BUYER AND IS IN LIEU OF ALL OTHER WARRANTIES, EXPRESSED, IMPLIED, OR STATUTORY, INCLUDING ANY WARRANTY OF MERCHANTABILITY OR FITNESS FOR ANY PARTICULAR PURPOSE.**

The user assumes all responsibility and liability for proper and safe handling of the goods. Further, the user indemnifies TI from all claims arising from the handling or use of the goods. Due to the open construction of the product, it is the user's responsibility to take any and all appropriate precautions with regard to electrostatic discharge.

EXCEPT TO THE EXTENT OF THE INDEMNITY SET FORTH ABOVE, NEITHER PARTY SHALL BE LIABLE TO THE OTHER FOR ANY INDIRECT, SPECIAL, INCIDENTAL, OR CONSEQUENTIAL DAMAGES.

TI currently deals with a variety of customers for products, and therefore our arrangement with the user **is not exclusive.**

TI assumes **no liability for applications assistance, customer product design, software performance, or infringement of patents or services described herein.**

Please read the User's Guide and, specifically, the Warnings and Restrictions notice in the User's Guide prior to handling the product. This notice contains important safety information about temperatures and voltages. For additional information on TI's environmental and/or safety programs, please contact the TI application engineer or visit www.ti.com/esh.

No license is granted under any patent right or other intellectual property right of TI covering or relating to any machine, process, or combination in which such TI products or services might be or are used.

FCC Warning

This evaluation board/kit is intended for use for **ENGINEERING DEVELOPMENT, DEMONSTRATION, OR EVALUATION PURPOSES ONLY** and is not considered by TI to be a finished end-product fit for general consumer use. It generates, uses, and can radiate radio frequency energy and has not been tested for compliance with the limits of computing devices pursuant to part 15 of FCC rules, which are designed to provide reasonable protection against radio frequency interference. Operation of this equipment in other environments may cause interference with radio communications, in which case the user at his own expense will be required to take whatever measures may be required to correct this interference.

EVM WARNINGS AND RESTRICTIONS

It is important to operate this EVM within the input voltage range of 0 V to 5 V and the output voltage range of 0 V to 5 V.

Exceeding the specified input range may cause unexpected operation and/or irreversible damage to the EVM. If there are questions concerning the input range, please contact a TI field representative prior to connecting the input power.

Applying loads outside of the specified output range may result in unintended operation and/or possible permanent damage to the EVM. Please consult the EVM User's Guide prior to connecting any load to the EVM output. If there is uncertainty as to the load specification, please contact a TI field representative.

During normal operation, some circuit components may have case temperatures greater than 60°C. The EVM is designed to operate properly with certain components above 60°C as long as the input and output ranges are maintained. These components include but are not limited to linear regulators, switching transistors, pass transistors, and current sense resistors. These types of devices can be identified using the EVM schematic located in the EVM User's Guide. When placing measurement probes near these devices during operation, please be aware that these devices may be very warm to the touch.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2004–2011, Texas Instruments Incorporated

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Texas Instruments:](#)

[EV2300](#)